

## Appendix C Radvision® ECS Configuration Summary

This example assumes that the ECS has been installed, access has been gained and a password has been set. Where an option is not mentioned it can be ignored or left unchecked. Use the Upload button at the top left of the page to save all changes, as you make them, and/or the Upload button at the bottom of configuration pop-up windows.

*Settings>Basics>Gatekeeper ID:* **gatekeeper-name**

*Settings>Basics>Dial Plan:* **Version 2**

*Settings>Basics>DHCP in the zone:* **Check/uncheck as appropriate**

*Settings>Basics>Who Can Register:* **Only Predefined Endpoints**

*Settings>Calls>Routing Mode:* **Direct**

*Settings>Calls>Accept calls:* **Checked**

*Settings>Calls>Immediate Call proceeding:* **Checked**

*Settings>Calls>Call Fallback:* **Reject the call**

*Settings>Capacity:* **enter values appropriate for your network topology and bandwidth availability**

*Settings> Dial Plan>Strip zone prefixes:* **Checked**

*Settings>Dial Plan>LRQ hop count:* **at least 9**

*Registration Restrictions>IP Range>Add:* **add subnets or endpoints by IP address, uploading each addition**

*Services>Services>Zone prefix 1>Edit:* **Prefix=0044xxxxx (substitute actual E.164 zone number supplied by JVCS-MC)**

*Hierarchy>Neighbors>Add>Prefix:* **0044**

*Hierarchy>Neighbors>Add>Description:* **text description (e.g. 'JVCS National directory')**

*Hierarchy>Neighbors>Add>IP Address:* **aaa.bbb.ccc.ddd (IP address supplied by JVCS)**

*Hierarchy>Neighbors>Add>Port:* **1719**

*Hierarchy>Neighbors>Add>Prefix:* **null (leave blank)**

*Hierarchy>Neighbors>Add>Description:* **text description (e.g. 'JVCS National directory 2')**

*Hierarchy>Neighbors>Add>IP Address:* **zzz.yyy.xxx.www (IP address supplied by JVCS)**

*Hierarchy>Neighbors>Add>Port:* **1719**

End of basic configuration.