

Appendix C – Radvision ECS Configuration Summary

This example assumes that the ECS has been installed, access has been gained and a password has been set. Where an option is not mentioned it can be ignored or left unchecked. Use the **Upload** button at the top left of the page to save all changes, as you make them, and/or the **Upload** button at the bottom of configuration pop-up windows.

Settings>Basics>Gatekeeper ID: **gatekeeper-name**

Settings>Basics>Dial Plan: **Version 2**

Settings>Basics>DHCP in the zone: **Check/uncheck as appropriate**

Settings>Basics>Who Can Register: **Only Predefined Endpoints**

Settings>Calls>Routing Mode: **Direct**

Settings>Calls>Accept calls: **Checked**

Settings>Calls>Immediate Call proceeding: **Checked**

Settings>Calls>Call Fallback: **Reject the call**

Settings>Capacity: **enter values appropriate for your network topology and bandwidth availability**

Settings> Dial Plan>Strip zone prefixes: **Checked**

Settings>Dial Plan>LRQ hop count: **at least 9**

Registration Restrictions>IP Range>Add: **add subnets or endpoints by IP address, uploading each addition**

Services>Services>Zone prefix 1>Edit: **Prefix=0044xxxxx** (substitute actual E.164 zone number supplied by JVCS-MC)

Hierarchy>Neighbors>Add>Prefix: **0044**

Hierarchy>Neighbors>Add>Description: **text description** (e.g. 'JVCS National directory')

Hierarchy>Neighbors>Add>IP Address: **aaa.bbb.ccc.ddd** (IP address supplied by JVCS)

Hierarchy>Neighbors>Add>Port: **1719**

Hierarchy>Neighbors>Add>Prefix: **null** (leave blank)

Hierarchy>Neighbors>Add>Description: **text description** (e.g. 'JVCS National directory 2')

Hierarchy>Neighbors>Add>IP Address: **zzz.yyy.xxx.www** (IP address supplied by JVCS)

Hierarchy>Neighbors>Add>Port: **1719**

End of basic configuration.

Source URL: <https://community-stg.jisc.ac.uk/library/janet-services-documentation/appendix-c-%E2%80%93-radvision-ecs-configuration-summary>